



Asus CW100 - Wireless Keyboard And Mouse Set Manual

Contents

[1 Specifications summary](#)

[2 Installing the batteries](#)

[3 Adjusting DPI](#)

[4 Keyboard hotkeys](#)

[5 Documents / Resources](#)

[5.1 Download manual](#)

Specifications summary

Model:	Mouse: CW100-M	Keyboard: CW100	Wireless Receiver: CW100-D
Hardware Version:	Mouse: 0.6	Keyboard: 1.0	Wireless Receiver: VER01
Software Version:	Mouse: V3.4.9	Keyboard: 1.0.3	Wireless Receiver: 1.96E
UKCA RF Output table (The Radio Equipment Regulations 2017)			
Max Output Power (EIRP):	Mouse: 0 dBm	Keyboard: 0 dBm	Wireless Receiver: 0 dBm
Operating Frequency Range:	Mouse: 2402 MHz - 2480 MHz	Keyboard: 2404 MHz - 2478 MHz	Wireless Receiver: 2402-2480 MHz
CE RED RF Output table (Directive 2014/53/EU)			
Max Output Power (EIRP):	Mouse: 0 dBm	Keyboard: 0 dBm	Wireless Receiver: 0 dBm
Operating Frequency Range:	Mouse: 2402 MHz - 2480 MHz	Keyboard: 2404 MHz - 2478 MHz	Wireless Receiver: 2402-2480 MHz
Frequency Deviation:	+/- 50KHz	+/- 50KHz	+/- 50KHz
Modulation Type:	GFSK		

Mouse Resolution:	800 / 1000 / 1200 DPI		
Battery:	Mouse - AA battery x1; Keyboard - AAA battery x1		
Power Rated:	1.5V (Keyboard) / 1.5V (Mouse) / 5V (Dongle)		
Operation Distance:	Keyboard - 10M without signal disturbance and no direction limit Mouse - 10M without signal disturbance and no direction limit		
Keyboard Dimension:	445.11mm x 133.21mm x 26.82mm; Weight: 489.5g (without battery)		
Mouse Dimension:	112.55mm x 60.01mm x 36.77mm; Weight: 58.8g (without battery)		
Dongle Dimension:	19.52mm x 15.70mm x 6.5mm; Weight: 1.9g		
Operating Temperature:	+5°C ~ +40°C	Storage Temperature:	-20°C ~ +55°C

Package contents:

CW100 Keyboard*1, CW100 Mouse*1, USB dongle*1 (stored inside the mouse), Quick Start Guide*1, Warranty booklet*1, AAA Alkaline Battery*1, AA Alkaline Battery*1

Installing the batteries

1. Insert the batteries (one AAA battery for keyboard and one AA battery for mouse) into the battery slots of your keyboard and mouse.
 - The low battery indicator of the mouse is beneath the scroll wheel and that of the keyboard is above the numeric keypad.
 - Please replace the battery when the low battery indicator flashes red.
2. Insert the bundled USB dongle into your computer's USB port. It takes about ten seconds for the system to automatically connect to your wireless keyboard and mouse.

Your keyboard and mouse is set at the factory to automatically connect to the system. You do not need to press the Connect button on your keyboard and mouse to manually connect to the system.

Adjusting DPI

To change the DPI, press the middle and the right buttons on the mouse simultaneously for 3 seconds to toggle between 800dpi, 1000 dpi (default) and 1600 dpi.

Keyboard hotkeys

Hotkeys

- <Fn+F1>: My Music
- <Fn+F2>: Volume
- <Fn+F3>: Volume +
- <Fn+F4>: Mute
- <Fn+F5>: Previous Track
- <Fn+F6>: Play/Pause
- <Fn+F7>: Next Track
- <Fn+F8>: Open Project settings
- <Fn+F9>: Screenshot
- <Fn+F10>: Open Task View
- <Fn+F11>: My PC
- <Fn+F12>: Calculator

- All above hotkeys can work with Windows® 10
- CW100 is compatible with Windows® 10 and older versions. Some hotkeys only work with Windows® 10. User experience may vary depending on the OS.

Q18681 / First Edition / July 2021

Documents / Resources

Download manual

Here you can download full pdf version of manual, it may contain additional safety instructions, warranty information, FCC rules, etc.

[Download Asus CW100 - Wireless Keyboard And Mouse Set Manual](#)

Need Assistance?

Do you have a question about the CW100 that isn't answered in the manual? Leave your question here.

■ ■

Stay updated with the latest solutions
Submit your question

Related Manuals for Asus CW100

[Computer Accessories Asus Audio Cover CA71 User Manual](#)

(112 pages)

[Computer Accessories Asus Chromebit CS10 Quick Start Manual](#)

(2 pages)

[Computer Accessories Asus CA81 User Manual](#)

Audio cover (112 pages)

[Computer Accessories Asus CW101 Quick Start Manual](#)

Wireless keyboard and mouse set (2 pages)

[Computer Accessories Asus Prime AP201 User Manual](#)

(32 pages)

[Computer Accessories Asus Eee Keyboard & Mouse Kit Manual](#)

(2 pages)

[Computer Accessories Asus ROG-THOR Series Quick Start Manual](#)

Power supply unit (141 pages)

[Computer Accessories Asus P2000 User Manual](#)

Keyboard and mouse set (2 pages)

[Computer Accessories Asus TUF Gaming GT 501 User Manual](#)

(28 pages)

[Computer Accessories Asus Varidrive Installation Manual](#)

Varidrive (4 pages)

[Computer Accessories Asus VENTO 3600 Quick Start Manual](#)

(2 pages)

[Computer Accessories Asus W3000 Quick Start Manual](#)

Wireless keyboard & mouse kit (2 pages)

[Computer Accessories Asus TA-55 User Manual](#)

Screwless model (2 pages)

[Computer Accessories Asus Xonar HDAV 1.3 Slim Quick Start Manual](#)

Av card (44 pages)

[Computer Accessories Asus Eee Keyboard + Mouse Set User Manual](#)

(43 pages)

[Save Article as PDF](#)